How-To: Universal AP convert HiveOS to WiNG OS 7 via CLI

Connect the console	Start Putty	Com # Speed 9600	
Login	Username: admin Password: aerohive		
Check firmware version	Show version	Version: HiveOS 10.2r4 (or higher)	
WiNG boot-os ready for reboot	_system boot-os WiNG		
Restart in recovery mode	Reboot		
Confirm reboot	Y		
Connect the console	Start Putty	Com # Speed 115200	
Login	Username: admin Password: admin123	BusyBox v1.17.4 built-in shell (ash) Enter 'help' for a list of built-in commands.	
Enter Standalone mode	AP adoption discovery process in progress... To cancel and boot in Standalone mode, type (s):	S	
Enter console mode	Please press Enter to activate this console.	"Enter"	
Inloggen	Username: admin Password: admin123	Enter and confirm new password	Password: test Password: test
Check firmware version	Show version	Version 7.5.0.0-005R (or higher)	

Questions or need advice? Get in touch with our experts!
Phone: +31 (0)70 764 06 00
E-mail: Support@kappadata.nl

Kappa Data
Laan van Zuid Hoorn 51
2289 DC Rijswijk